PSESMB 200W - Power Supply



- AC Input Range Selectable By Switch
- Short Circuit/Overload/ Over Voltage/ Over Temperature Protection
- Cooling By Free Air Convection
- Withstand 300VAC Surge Input For 5 Seconds
- · Built-in Constant Current Limiting Circuit
- LED Indicator for Power On
- 100% Full Load Burn-in Test
- 5G Anti-Vibration Capability
- No Load Power Consumption Less Than 0.75W
- Operating Temperature Range: -25°C to 70°C



Anaheim Automation's PSESMB series is a cost-effective choice for your power supply requirements. This power supply provides up to 200Watts of power at voltages of 24, 36 and 48VDC with a switch selectable input range of 90-132VAC to 180-264VAC. Each power supply is equipped with an LED indicator for power on in addition to short-circuit, overload, and over voltage protection features. Compact in size and affordably priced, they provide up to 90% efficiency, high reliability, and a long lifetime.

INPUT						
Voltage Range (VAC)	Voltage Range (VDC)	Frequency Range	Efficiency	AC Current	Inrush Current (Cold Start)	Leakage Current
90~132 VAC/ 180~264 VAC selected by switch	240~370	47~63 Hz	89.5-90%	4A/115VAC 2.2A/230VAC	60A/115VAC 60A/230VAC	<2mA/240VAC

OUTPUT											
Part Number	DC Voltage	Rated Current (A)	Current Range (A)	Rated Power (W)	Ripple & Noise	Voltage Adj. Range (V)	Voltage Tolerance	Line Regulation	Load Regulation	Setup, Rise Time	Hold Time
PSESMB-0200-1-24V-8.8A	24V	8.8	0~8.8	211.2	150mVp-p	21.6~28.8	±1.0%	±0.5%	±0.5%	1500ms, 50ms/230 VAC	16ms/230 VAC
PSESMB-0200-1-36V-5.9A	36V	5.9	0~5.9A	212.4	200mVp-p	32.4~39.6	±1.0%	±0.5%	±0.5%	1500ms, 50ms/230 VAC	16ms/230 VAC
PSESMB-0200-1-48V-4.4A	48V	4.4	0~4.4	211.2	200mVp-p	43.2~52.8	±1.0%	±0.5%	±0.5%	1500ms, 50ms/230 VAC	16ms/230 VAC

L011590

Units: mm 32.5 150 o LED □åĎj. S 35 5 **⊕** 3 2 32.5 4 15

Terminal Pin No. Assignment:

	-		
Pin No.	Assignment	Pin No.	Assignment
1	AC/L	4~6	DC OUTPUT -V
2	AC/N	7~9	DC OUTPUT+V
3	FG ≟		





